2-COLOUR ELECTRICAL NETWORK ANALYSER

DIVA105C

*The DIVA105C is a high accuracy **electrical network analyser**, with **IP 65** front face protection.*
Each appliance is equipped with a two-colour 4 digits 14 mm high display with a brightness which
Integrates perfectly in applications in industrial control rooms.
The extra-thin front face allows a better integration in cabinet fronts.
They allow the display, the control and the transmission of all the parameters of DC electrical networks.

Two display versions are available:



Two-colour display, red and green





Two-colour display, red and white



Introduction

- **Inputs:**

  Network type: DC
  Voltage, current and power measurement
  2 voltage calibres: 150 / 400 V
  2 current calibres on external shunt: 20 mV / 100 mV

- **Universal power supply**

  20 to 250 VAC and 20 to 250 VDC

- **Options:**
  (Specify on order)
  - **Isolated analogue output**
    Active current output, or voltage output.
  - **Output 2 or 4 relays**
    Mode setpoint or window.
  - **Isolated digital communications**
    RS485 2-wire, protocol MODBUS-JBUS
  - **2 isolated logic inputs (24VDC signal)**
  - **16-leds bar graph display**

Easy programming on front face with a 5-key tactile keyboard, or via the software SlimSET with a standard USB-µUSB cable (optional).

- **Display**:
  Electroluminescent red and green (or red and white)
  Selection of the basic colour and the condition for colour change programmable.
  ±10000 points.
  4 alarm leds.
  Possibility to programme 3 magnitudes for display, accessible simply by pressing 1 key.

- **Housing**: Self-extinguishing case of black UL 94 V0 ABS.
  Extra-thin 1.4 mm front face

- **Connectors**: Removable terminal blocks on rear face for screwed connectings (2.5mm², flexible or rigid).

- **Protection**: Front face: IP 65 Housing/terminals: IP20

- **Compliance with standards**:
  Directive LV 2014/35/UE.....EN 61010-1
  Directive EMC 2014/30/UE.....EN 61326-1
  Directive ROHS 2011/65/UE

CE Marking

sfere
69510 SOUCIEU EN JARREST - Tél. : 33 (0)4 72 31 31 30 Fax. : 33 (0)4 72 31 31 31

Technical features

Types of inputs

DIVA105C

- 2 voltage calibres (programmable): 150V and 400V.
  Un = 150 VDC and 400 VDC
  Overrange: 1.2 Un
- 2 current calibres (programmable) on external shunt:
  20 mV and 100 mV.
  Overrange: 1.2 In
- Accuracy rating:
  Class 0.2 for voltage / current (at 25°C)
  Class 0.5 for the powers
- Measure cycle: 50 ms
- Thermal drift < 200 ppm/°C
- Digital filtering programmable
- Input impedance:
  > 2 MOhms for the voltage input.
  < 0.2 VA for the current input.

Types of options

option A1,A2,A3

Analogue output: 3 types on choice

A1: Active current output 0/4-20mA
A2: Passive current output 0/4-20mA
A3: Voltage output 0-10V

- Accuracy: 0.1 % in relation to the display (at +25°C)
- Residual ripple ≤ 0.2%
- Admissible load 0Ω < Lr < 600 Ω (current)
  Lr > 5kΩ (voltage)
- Scale ratio programmable with enlarging effect.
- Response time: 40 ms

option R, R4

Relay outputs:

2 or 4 independently programmable relays

Alarm mode:

- Hysteresis programmable independently in display points
- Time delay programmable independently from 0 to 999.9 s in 0,1s. increments.

Break-make contact 8 A - 250 V on resistive load

Pulses mode:

- Width and weight of the pulse adjustable.

option N

Digital output:

- RS485 2-wire, protocol MODBUS-JBUS
- Slave number programmable from 1 to 255.
  Baud rate from 1200 to 19200 bauds

option T

2 logic inputs: 24 VDC signal

0 reset of the min. and max.

option B

16-leds bargraph display:

- Quick evaluation of the variations of the measured value.
  Scale factor programmable.

Power supply

20 to 250 VAC 50/60Hz, and 20 to 250 VDC

Power consumption: 3 W max. 6 VA max.

Galvanic isolation

3 kVeff 50HZ 1mn, between supply, voltage input, current input, analogue output, relay outputs, RS485 output and logic inputs.

1.5 kV between analogue output and RS485.

♦ Integration indice (programmable)

Allows stabilizing the display in case of unsteady input.

♦ Self-diagnosis

- Self-diagnosis detection of the errors programmable on the 2 relays.
- Fall back value programmable on the analogue output in case of self-diagnosis error.

♦ Brightness setting

Setting of the digits brightness programmable on 4 levels, depending on the location of the device (outdoor, control room...)

♦ Quick reading on the display

- Of the value of the setpoints.
- Of the min. and max. values

♦ Function simulation

- Possibility to simulate the analogue output (generator mode).
- Simulation of the relays.

♦ Changing of the display colour

- Programming of the main display colour.
  Programming of the display colour change on alarm or self-diagnosis

♦ Access code

An access code adjustable from 0000 to 9999 serves to protect the digital panel meter from unauthorized programming and to lock the access to some functions.

On factory exit the code is 0000.

Programming of the functions accessible by code.

Environment

- IP65 front face protection.
- Operating temperature: -20 to +60°C.
- Storage temperature: -20 to +70°C.
- Relative dampness: 80% annual average.
- Use in pollution degree 2 and voltage surge category II or better for 500 V AC, and III or better for a voltage lower than 300 V AC.
- Max. altitude: 2000 m
- Weight: 150g (with packaging)

Coding

♦ Type: DIVA105C

♦ **Output options***:*
A : Analogue (A1, A2 or A3: specify)
R : 2 relays
R4: 4 relays
N : Digital communications RS485
T : 2 logic inputs
B : Bar graph display


All outputs can be combined except for the configuration: AR4NT.


♦ **Colour code:**
RG: Two-colour display, Red/Green
RW: Two-colour display, Red/White

♦ Order example :
For a two-colour analyser in Red/Green with active current analogue output and 2 relays, request the reference:
DIVA105C A1R RG.

Dimensions

Housing: 96 x 48 x 119.4 mm (with terminals)






Mounting: on panel, cut out 43 x 91.2 mm


This appliance is dedicated to industrial applications. It has to be installed in an electrical cabinet, or equivalent.

Connectings




Location of the terminals
(view of case rear side)


INPUTS




OUTPUTS (optional)

ANALOGUE OUTPUT D






RELAYS 1 AND 2 C




RELAYS 3 AND 4


F




E




RS485 G




LOGIC INPUTS G or **LOGIC INPUTS** F





SUPPLY

A



Recommendations for the wiring:
The input network may carry significant disturbances, and this may disturb the complete chain.
In order to avoid this, the immunity from parasites may be made significantly better by respecting the following rules:
- Do not connect too close: the input network and the wires of the DIVA105C power supply.
- Do not connect too close: the input network and all the DIVA105C output wires.
- Use for all the outputs of the DIVA105C shielded cables connected to the GND on both ends.

sfere

e-mail : info@ardetem.com
www.ardetem-sfere.com

Route de Brindas
Parc d'activité d'Arbora N°2
69510 SOUCIEU EN JARREST
FRANCE

Tél. : 33 (0)4 72 31 31 30
Fax. : 33 (0)4 72 31 31 31

your representative

SFERE - CA IN/72 - A 03/24 – Any data in this documentation may be modified without prior notice.